

# BUMP FEED WIND5

## BUMP & FEED type

Diameter : 5-1/2"  
 Weight : 450g  
 Spool capacity :  $\Phi 2.4 \times 7m$   
 Suitable engine : 30~45cc

- \* Low Vibration
- \* Open Eyelet
- \* Divided Line Holder
- \* High Durability
- \* Winding System
- └ Easy to Wind Line

### FEMALE HEADS

| Model Code | Size                 |
|------------|----------------------|
| W5-08125NL | M8 X P1.25LH female  |
| W5-1010NL  | M10 X P1.0LH female  |
| W5-10125NL | M10 X P1.25LH female |
| W5-1015NL  | M10 X P1.5LH female  |
| W5-12125NL | M12 X P1.25LH female |
| W5-1215NL  | M12 X P1.5LH female  |
| W5-12175NL | M12 X P1.75LH female |

### MALE HEADS

| Model Code | Size               |
|------------|--------------------|
| W5-08125BL | M8 X P1.25LH male  |
| W5-10125BL | M10 X P1.25LH male |

If you need other size, please contact us.

- ①  
Set the line with ▼ mark and insert line



- ②  
Pull line out

- ③  
Wind line



### Adapter Bolts



M8 x P1.25LH  
 M10 x P1.25LH



M10 x P1.25LH  
 M10 x P1.25LH

### Parts List

| No. | Parts Name  | Q'ty |
|-----|-------------|------|
| ①   | Screw       | 2    |
| ②   | Case Cover  | 1    |
| ③   | Case        | 1    |
| ④   | Eyelet      | 2    |
| ⑤   | Line Holder | 1    |
| ⑥   | Nut         | 1    |
| ⑦   | Nylon Line  | 1    |
| ⑧   | Spring      | 1    |
| ⑨   | Cover       | 1    |

